


CE
0051

Endo Motor MotoSync Pro[®]

Manual




Please read this manual before operating.



1. Scope of MotoSync Pro


1.1 Parts Identification



NOTE

- The USB port on the Handpiece is only used to connect to the Adapter

1.2 Components and Accessories




Motor Handpiece (1pcs)




Base (1pcs)



Contra Angle (1pcs)



Adapter (1pcs)



Measuring wire (1pcs)



Lip Hook (2pcs)



File clip (2pcs)



Insulating Sleeve (1pcs)



Spray Nozzle (1pcs)

1.3 Options (sold separately)



Disposable Sleeve



Apex Tester (1pcs)

2. Symbols used in the User Manual

	Manufacturer's LOGO
 WARNING	If the instructions are not followed properly, operation may lead to hazards for the product or the user/patient.
 NOTE	Additional information, explanation of operation and performance.
	Serial number
	Catalogue number
	Manufacturer
	Date of manufacture
	Safety class II device
	Type B applied part
	CE marking
	Direct current
	Do not dispose of with normal household waste
	Store in a dry place
	Consult instructions for use
	Can be autoclaved up to a maximum temperature of 134° Celsius
	Authorized Representative in the European Community
	Manufacturer
	Unique Device Identification

3. Before Use

3.1 Intended Use

MotoSync Pro is exclusively designed for dentists for use with dental root canal instruments in continuous rotation and in reciprocating movement with integrated apex locator.

It is a cordless Endo Motor And Apex Locator with root canal measurement capability. It can be used as a Endo Motor And Apex Locator for preparation and enlargement of root canals, or device for measuring canal length. It can be used to enlarge the canals while monitoring the position of the file tip inside the canal.

This device must only be used in hospital environments, clinics or dental offices by qualified dental personnel.

3.2 Contraindications

The integrated apex locator of the MotoSync Pro is contraindicated in cases where patient/user carry medical implants such as pace makers or cochlear implants etc.

Do not use the device for implants or other non-endodontic dental procedures.

Safety and effectiveness have not been established in pregnant women and children.



WARNING


Read the following warnings before use:

- 1. The device must not be placed in humid surroundings or anywhere where it can come into contact with any type of liquids.*
- 2. Do not expose the device to direct or indirect heat sources. The device must be operated and stored in a safe environment.*
- 3. The device requires special precautions with regard to electromagnetic compatibility (EMC) and must be installed and operated in strict compliance with the EMC information. In particular, do not use the device in the vicinity of fluorescent lamps, radio transmitters, remote controls, portable or mobile RF communication devices and do not charge, operate or store at high temperatures. Comply with the specified operating and storage conditions.*
- 4. Manufacturers can provide circuit diagrams, component lists, drawing notes, calibration rules as required.*
- 5. Do not disassemble the battery without authorization, otherwise it will cause short circuit or electrolyte leakage. Do not place the battery in a location where it is difficult to disconnect the adapter.*
- 6. Gloves and a rubber dam are compulsory during treatment.*
- 7. If irregularities occur in the device during treatment, switch it off. Contact the agency, the surface temperature of the application part may reach 51 °C.*
- 8. Never open or repair the device yourself, otherwise, void the warranty.*


4. Installing the MotoSync Pro

4.1 Installation of the contra angle

Make sure 3 pins on contra angle alignment the slots of handpiece, plug them together until it "click" securely into place.



The contra angle can be 360 degrees rotated without take off, make it easy to watch the LCD in treatment by rotating the contra-angle.



WARNING

- *Make sure the assembly is connected properly, otherwise might cause unexpected motor reverse, even hurt the patients After connecting the contra angle and handle, pull it gently to make sure the connection is good.*
- *The improve insulation of the contra angle during combine apex, we recommend using an insulating sleeve.*




You can also use disposable sleeve (sold separately) instead of insulating sleeve

NOTE

- *Without the insulating sleeve, when performing the apex measurement with handpiece, wear appropriate insulated gloves, and make sure the contra angle does not touch the lips.*
- *It is advisable to use a rubber dam when performing such treatments.*

4.2 Install the file

Turn the file back and forth until it is lined up with interior latch groove and slips into place, lock the file into the contra angle. Hold down the push button on the contra angle and can release the file.




WARNING

- *Inspect the file head before inserting the file. Do not use the damaged file head.*
- *Make sure the motor is stopped when inserting and removing files.*
- *Be careful when inserting and removing files to avoid injury to fingers.*
- *Take care not to touch the Main switch when putting files in. this will cause the file to rotate.*
- *Pull the file gently to make sure that the file is secure in handpiece properly, otherwise it may pop out and hurt the patient.*
- *Please use files with shanks meet the ISO standard. (ISO standard: O2.334 –2.350 mm)*


4.3 Connecting measuring wire

If want activity apex measurement function, uncap the USB cover on handpiece, insert measuring wire.




NOTE

- Match colors to connect the lip hook and file clip, if connect lip hook with black slot, apex auto start will have no function.



4.4 Connecting Charging

Using adapter connect to handpiece directly, the charge state will show on the screen.




NOTE

- The handpiece will not function during charging.
- Only the original adapter could be used.

5. Use Interface

5.1 Panel key



- ①  Main switch
- ② Display Screen
- ③  Setting key
- ④  Decrease key
- ⑤  Increase key

Turn Power On

Press  more than 0.5 seconds to turn on the instrument

Memory Change

Press  or  during standby state

Operation mode Change

Press  once during standby state, press  or  to change, then press  or wait 5 seconds to confirm

Parameter Adjustment

Press  till target parameters, press  or  to adjust, then press  or wait 5 seconds to confirm


Turn Power Off

Holding down press 

Advanced setting


During power off state, holding down press  then press  to entry advanced setting, Press  till target setting, press  or  to adjust, then press  to confirm

5.2 Screen display




Standby interface

- ① Memory mode number
- ② Speed of this memory program
- ③ Unit of speed: Revolutions Per minute
- ④ Residual battery power
- ⑤ Operation mode
- ⑥ Torque of this memory program
- ⑦ Unit of torque: Newton centimeter
- ⑧ Volume icon




Standard working mode

- ① The set maximum torque
- ② Real time torque
- ③ Torque display scale
- ④ The preset speed




Reference point interface

- ① Flash bar of apical reverse position
- ② Apex (Major/Anatomic apical foramen)
- ③ 0.5mm meter reading (Very near Minor/Physiological apical foramen)
- ④ 1mm-3mm (Estimate dimension) distance scale from apex (Estimate dimension)



Canal measurement standby interface

- ① Memory mode number M0 is apex stand-alone memory
- ② Electronic apex locator
- ③ Apex flash bar




Canal measurement start interface

① Indication number The number has no represent of actual length, only for indication

② Canal length indicator bar

③ Apex flash bar (apex stand alone mode) or reference point flash bar (motor combine with apex mode)



Canal measurement approach apex interface

① The estimate dimension from apex (Major/Anatomic apical foramen)

② Canal length indicator bar



NOTE


- The meter numbers 1.0, 2.0, 3.0 and digital numbers 00-16 do not represent the actual length from the apical foramen. It simply indicates the file progression towards the apex. The digital numbers -1 and -2 indicate that the file has passed the apex foramen. The digital number "00" indicate that the file has reached the apex foramen. Subtract 0.5-1mm from the measured file length as the working length. These numbers are used to estimate the canal's working length.

5.3 Terms and definition

Fwd	Forward (Clockwise rotation)
Rev	Reverse (Counter clockwise rotation) Be applied to special file, inject calcium hydroxide and other solutions
REC	Reciprocation Be applied to reciprocating file, path file and rotary file protection by setting some special angle
TAT	Torque adaptation technology Up to setting torque, the motor will move with reciprocating mode; when torque reduce to normal value, the motor will clockwise rotate
PPT	Precision path technology PPT's Role in Minimizing File Breakage PPT significantly lowers the risk of file fractures with its innovative reciprocating action. The challenging task of patency through manual filing is now accomplishable with an endo motor!
EAL	Electronic apex locator In the mode, the device will work like a stand-alone apex locator
AP	Apex Major apical foramen or Anatomic apical foramen
Reference point	During combined length determination, normally apical reverse must active before reaching major apical foramen, setting apical reverse position by change the flash bar
FWD Angle	Forward angle (Clockwise rotation angle), activating in REC and TAT operation mode
REV Angle	Reverse angle (Counter Clockwise rotation angle), activating in REC and TAT operation mode
Memory Mode	Such as M0-M10
Operation Mode	Such as FWD, REV, REC and TAT

6. Setting

6.1 Selecting memory



MotoSync has 10 memory programs, press **-** or **+** to change during standby state, the memory number (①) will change according.

M1-M9 is standard working memory for canal shaping, every memory has its own speed (②), mode (③) and torque (④), all this these parameters can be changed (**See chapter 6.2 Setting parameters**).



M0 is special memory for stand-alone apex locator function (See chapter 7.3 Apex operation and not suitable condition).

6.2 Setting parameters



Before start the motor, check the operation mode (①) is correct, otherwise press **S** once during standby state, press **-** or **+** to change.

Operaton Mode

FWD

MotoSync has 4 operation modes: FWD, REV, REC and TAT (See chapter 5.3 Terms and definition to get the explanations of these modes).



NOTE

- When choice REV mode, a slow beep alarm sound appears after starting the motor, used for indicating counter clockwise rotation happening.

Repeatedly press **S** to check all the next level parameters of this operation mode are expected, press **-** or **+** to change if not .



NOTE

- The parameter will differ in difference mode according to certain logic.

Speed Set

800 rpm

The speed setting can be adjusted from 50rpm-2500rpm.



NOTE

- The speed of REC and TAT peration mode is difference according to ertain logic (See chapter 6.5 Parameter logic).

Torque Limit

1.5 N·cm

0.4-5.0N·cm

The torque of REC and TAT operation mode is difference according to certain logic.



WARNING

- When choice R.L (torque reverse less), a slow beep alarm sound appears after starting the motor.
- Be careful to use this function, very professional skill is needed, otherwise has risk of file broken.

AUTO Start

ON

MotoSync Pro integrated apex locator, if the lip hook is connecting with patient's lip, when the endo file entering root canal, the motor will start automatically.

Press  or  to shut off this function if not expected, press  to start and stop the motor.



WARNING

- *The motor will start automatically if handpiece (without insulating sleeve) or file touch the patient's lip or operator's fingers (without insulating glove), take care to avoid this, the file rotated by motor has risk of injure someone.*

AUTO Stop

OFF

When the endo file out of root canal, the motor will not auto stop with default setting, Press  or  to select auto stop "ON" if needed.

Apical Action

Reverse

Because of integrated apex locator, when the file reaches the reference point, the motor will response according to setting, it can be Reverse, SlowDown, Stop and Off.



Press  or  to change.

Reverse: rotation direction changing till the file upward a little bit by operator, rotation direction will change back again.

SlowDown: rotation slowdown when approach the reference point, will reverse if reach.

Stop: rotation stop when reach the reference point, upward a little bit and will rotate again.

Off: rotating as usual even if reach the reference point.




During combined length determination, normally apical reverse must active before reaching major apical foramen, Press **-** or **+** to set apical reverse position by change the flash bar (①), the motor will reverse while reaching the flash bar every time.

Forward angle (Clockwise rotation angle) can be adjusted by operator from 10° to 400°, Press **-** or **+** to change.

Reverse angle (Counter Clockwise rotation angle) can be adjusted by operator from 10° to 400°, Press **-** or **+** to change.

6.3 Preset programs




For convenience, we preset some common file system.

Long press **S** to entry preset program during standby state, the interface will show as left.

M1 (①) meanings the current memory mode, you can replace it by preset program (②)

press **-** or **+** to change, then press **⏻** to confirm.



And the memory mode (①) will change according, also operation mode (②), speed (③) and torque limit (④) will change according to the file system default setting.



All of memory mode (from M1-M9) can be replaced with same method.

6.4 Advanced setting

Versions

E.1.1.008

Versions

V1.0

Auto Power Off

10 Min

Auto Return

10 S

Volume

Vol.2

Brightness

100%

During power off state, holding down press **S** then press **⏻** to entry advanced setting, the version number software will appear on the display screen.

Press **S** again, the "Auto Power Off" time can be change, press **-** or **+** to adjust, then press **⏻** to confirm.

The "Auto Power Off" time can be set from 3-15 minutes.

Press **S** again, the "Auto-Return" time can be change, press **-** or **+** to adjust, then press **⏻** to confirm.

The default value is 10s.

Press **S** again, the "Beeper Volume" can be change, press **-** or **+** to adjust, then press **⏻** to confirm.

The "Beeper Volume" can be set from 0-3.

Press **S** again, the "Brightness" can be change, press **-** or **+** to adjust, then press **⏻** to confirm.

The "Brightness" can be set from 25%-100%.

Habit hand

Right Hand

Press **S** again, the "Habit hand" can be change, press **-** or **+** to adjust, then press **U** to confirm.

The right hand and the left hand can be set.

Calibration

OFF

Press **S** again, entry "Calibration" function, press **-** or **+** to select "ON", press **U** to start calibration.



WARNING

Before calibrating, making sure the original contra angle is installed, and do not install the file.

The torque will not correct if calibration without original contra angle or any load on contra angle chuck, and has risk of file broken.

Restore settings

OFF

Press **S** again, entry "Restore setting" function, press **-** or **+** to select "ON", press **U** to start recovering, all the parameters be set by operator will be recovered by default factory setting.



NOTE

After restore setting, all the parameters will be covered, record what you need before this operation.


Language

English


Press **S** again, the "Language" can be change, press **-** or **+** to adjust, then press **U** to confirm.

7. Operation

7.1 Charge

	<p>Displays the present remaining amount of the battery. Less than 15% remains, please charge.</p> <p> NOTE</p> <ul style="list-style-type: none">• If the power is less than 15%, must be recharged within 30 days, otherwise the battery will be damaged.
<p>Low Power Please Charge</p>	<p>If continue to use, the torque and speed will low than the setting value, and low power warning will appear on screen, and the device will stop work.</p> <p> NOTE</p> <ul style="list-style-type: none">• The remaining amount of battery mark indicates a voltage.• When a load is applied to the motor handpiece, the remaining amount of battery mark appears to become lower.
	<p>Charging indication appears on the screen, and flashes slowly (①), when battery is fully charged or in a state near full charge, the flash will stop and show like picture (②).</p> <p>Fully charged will take about 4 hours, depending on residual battery power and battery state.</p> <p>It can be recharged 300-500 times, depending on the operating conditions of the device.</p> <p> NOTE</p> <ul style="list-style-type: none">• When changing, other function will forcibly stop. <p> WARNING</p> <ul style="list-style-type: none">• Do not change the battery, only trained technician or distributor can change the battery, the electronic parts will be damaged if use a wrong battery or install with a wrong way

7.2 Motor operation




When using as a stand-alone motor, the torque will show on the screen (**more information about torque bar, please see chapter 5.2 Screen display**).




WARNING

- Use the MotoSync Pro outside the oral cavity to make sure that the device is functioning properly.
- Change file on time to avoid file separation within the canal. File may separate because of cyclic / torsional fatigue.
- Heavy force / hand pressure on endo motor while using may even cause file separation.
- Do not press the button to release the files while the motor is running, otherwise the file may pop out and even hurt the patient.
- Electromagnetic noise in surroundings environment may interfere with the device operation, do not rely on device's automatic control completely, always pay attention to the feedback from display.



When using motor combine apex function, the measure wire must be connecting with motor by USB socket, and white slot connects with lip by lip hook, keep the black slot idle.

The reference point bar will show on the screen (**more information about reference point bar, please see chapter 5.2 Screen display**).



NOTE


- We strongly recommend check the function every time before use.
- Touch the lip hook with the file in the contra angle and check that all the bars on the meter on the screen light up, and the motor should be reversed continuously



NOTE

- The will not be able to perform a precise measurement for every time, especially in cases of abnormal or unusual morphology of the root canal. The user need coordinate with x-ray to check the results of the measurement.
- If the meter does not move when you enter the file, it is possible that the unit is not working normally, therefore, stop using.


7.3 Apex operation and not suitable condition




When using as a stand-alone apex locator. We suggest put the handpiece on the Base to get better visual angle.

The measure wire must be connecting with motor by USB socket, white slot connects with lip by lip hook, and black slot connect with file clip.

The canal length indicator bar will show on the screen (**more information about canal length indicator bar, please see chapter 5.2 Screen display**).




The reference point can be adjusting when use stand-alone apex function. Press **S** to active reference point interface during M0 standby state, Press **-** or **+** to change reference point by change the flash bar (①), a continuous beeping will appear when reach the reference point.




NOTE

- The file clip must hold the file correctly.
- Push the button of file clip in the direction shown by the arrow, clip the holder onto the metal upper part of the file and then release the button.
- The file clip must be nearly vertical with file handle, otherwise will damage the tip of the file holder.



NOTE

- We recommend using Apex Tester to check the accuracy of apex locator every time before use.
- Insert the Apex Tester into handpiece USB socket during M0 mode, check the highlight number must between -1 to 1



NOTE

- We recommend check the connection of apex locator every time before use.
- Touch the lip hook with metal part of file clip, check all the bars on the meter on the screen light up, and "-2" flash on the top.


Unsuitable situation of root canals for Electric Measurement

Cannot obtain precise measurements if the root canal conditions as below



Root canal with a large apical foramen

- The root canal cannot be accurately measured because of the lesion or incomplete development of the apical foramen.
- The results may show that the length measured is shorter than the actual one.




Root canal blood overflow from the opening

- If blood spills from the root opening and contacts the gums, it will cause leakage of electricity, which cannot be accurately measured.
- Wait for the bleeding to stop completely. Clean the root canal and the opening, completely empty the root canal blood, and then measure it.





The root canal uses a chemical solution to flow out from the opening





- If a chemical solution flows out of the root canal, it is impossible to get an accurate measurement. It is important to remove the overflow from the opening.



Broken crown

- If the crown is broken, a segment of the gingival tissue enters the lumen, and the contact between the gingival tissue and the root file causes electrical leakage, which cannot be accurately measured.
- In this case, the appropriate material should be used to isolate the gingival tissue.

 <p>Crack</p> <p>Branch</p>	<p>The crack tooth Leakage through branch of the root canal</p> <ul style="list-style-type: none"> • Broken teeth can cause electrical leakage and cannot be accurately measured. • Branch tubes can also cause leakage.
 <p>Gutta-percha</p>	<p>Retreatment canal which was filled with gutta-percha</p> <ul style="list-style-type: none"> • The gutta-percha must be completely removed to eliminate its insulation, then pass a small file all the way through the apical foramen and then put a little saline in the canal, but do not let it overflow the canal opening.
 <p>Crown</p>	<p>Crown or metal prosthesis that touches gingival tissue</p> <ul style="list-style-type: none"> • Accurate measurement cannot be obtained if the file touches a metal prosthesis that is touching gingival tissue. In this case, widen the opening at the top of the crown so that the file will not touch the metal prosthesis before taking a measurement.
 <p>Debris</p> <p>Pulp</p>	<p>Cutting debris on tooth Pulp inside canal</p>

<p>Caries touches gums</p> 	<p>Caries touching the gums</p> <ul style="list-style-type: none"> In this case, electrical leakage through the caries infected area to the gums are impossible to obtain an accurate measurement.
 <p>Blocked</p>	<p>Blocked canal</p> <ul style="list-style-type: none"> The meter will not run if the canal is blocked. Opening the canal all the way to the apical constriction to measure it.
 <p>Too dry</p>	<p>Extremely dry canal</p> <ul style="list-style-type: none"> If the canal is extremely dry, the meter may not work until it is quite close to the apex. In this case, try to moisten the canal with oxydol or saline.
<p>Difference measuring result between Apex locator reading and Radiography</p> <p>Sometimes the reading of the apex locator reading does not correspond to the X-ray image. this does not mean inaccurate of apex locator or X-ray, depending on the angle of the X-ray beam, the root tip may not be displayed correctly. The position of the root tip seems to differ from its true position.</p>	
 <p>X-ray photo</p> <p>X-ray tube</p>	<p>The X-ray photo shows that the actual apex of the root canal is not the same as the anatomic end. In fact, the apical foramen is located at the coronal end. in this case, X-ray may indicate that the file needle has not reached the apical foramen, even if it has actually reached the apical foramen.</p>

8. Maintenance

Autoclavable Components

Contra Angle



Lip Hook



File clip




Insulating Sleeve



WARNING

Only the components above can be autoclaved.

Autoclavable Procedure



Cleaning: Clean the components with running water with a soft cloth.

Disinfection: Wipe the components with a piece of gauze that has been dampened with Ethanol for Disinfection (Ethanol 70 to 80 vol%) and wrung out thoroughly.

Lubrication: Only the contra angle needs to be lubricated



Before autoclaving, the contra angle must be lubricated.

Attaching the spray nozzle to oil can and contra angle, press the oil can button more than 3 seconds, till all the black oil flow out from the head of the contra angle.

Packing: Pack the components in “Sterilization pouches”.

Sterilization: Steam sterilization at 134°C at least 4 minutes or

steam sterilization at 121°C at least 35 minutes.

Minimum drying time after sterilization: 10 minutes.

Storage: Keep the components in sterilization packaging in a dry and clean environment.

Processing limit

The products have been designed for a large number of sterilization cycles. The materials used in manufacture were selected accordingly. However with every renewed preparation for use, thermal and chemical stresses will result in ageing of the products. The maximum number of sterilizations for products is 250 times.



WARNING

- *Comply with your national guidelines, standards and requirements for cleaning, disinfection and sterilization.*
- *Be careful to avoid cross contamination when performing maintenance.*
- *Must be autoclaved after use for each.*
- *Do not lubricate the motor handpiece.*

Environmental protection

The instrument does not contain harmful ingredients and can be disposed of and destroyed in accordance with relevant local regulations.

Disinfection components


Motor Handpiece




Base



Adapter



Measuring Wire



Wipe the components with a piece of gauze that has been dampened with Ethanol for Disinfection (Ethanol 70 to 80 vol%) and wrung out thoroughly.



NOTE

- Do not use anything except Ethanol for Disinfection (Ethanol 70 to 80 vol%).
- Do not use too much ethanol as it's going into machine and damage the components inside.

Single-use component

Disposable Sleeve



NOTE

- Single-use handle sleeve must be disposed of and changed after every treatment.
- In the event of non-compliance, the contamination risk increases.

9. Error Warning

<p>Overload Restart Motor</p>	<ul style="list-style-type: none">• During reverse processing, the Overload warning may appear on the screen, it means a large load happened greater than the motor force.• Press the Main switch to restart motor.
<p>LowPower Please Charge</p>	<ul style="list-style-type: none">• The power is very low, charge it immediately

10. Troubleshooting

When trouble is found, check the following points before contacting your distributor. If none of these are applicable or the trouble is not remedied even after action has been taken, the product may have failed. Contact your distributor.

Problem	Cause	Solution	Ref. chap
The power is not turned on.	The battery is flat.	Charge the battery.	7.1
	Press the main switch too short time.	Press the main switch more than 0.5 seconds.	5.1
The motor doesn't rotate.	M0 mode is stand-alone apex locator function.	Changing to M1-M9.	6.1
	The contra-angle is clogged	Clean or replace the contra-angle.	/
	Motor is protected by system or broken.	Check the error warning.	9
Motor does not run when the file is inserted in the canal.	The measure wire connecting not properly.	Check the connection.	4.3
	The lip hook not properly hooked in the corner of the patient's mouth.	Check the connection.	7.2 7.3
	The Auto start function is OFF	Turn the auto start Function ON if necessary.	6.2
The motor Can't stop.	The Auto stop function is OFF.	Press main switch to stop it, setting Auto stop function ON if necessary.	6.2
	There is a short circuit inside the motor handpiece or the motor handpiece cord.	Press "S" button to stop the motor and contact your distributor.	/

Motor spontaneously starts running in reverse.	Up to setting torque limit.	Check the torque limit is enough or not.	6.2
	Apical action setting to Reverse	Change setting if it's not expected.	6.2
	Setting to REV mode.	Change setting if it's not expected.	6.2
Motor does not reverse.	Torque reverse setting might be too high.	Change setting if it's not expected.	6.2
	Apical action setting Stop or OFF.	Change setting if it's not expected.	6.2
Motor speed changes spontaneously	Apical action setting Slow Down.	Change setting if it's not expected.	6.2
Motor alternates between forward and reverse rotation.	Operation mode setting to REC or TAT.	Change setting if it's not expected.	6.2
No sound.	Beep volume set to 0.	Set beep volume to 1, 2 or 3.	6.4
Canal measurement is unstable.	Complex root canal environment.	Check situation of root canals.	7.3

11. Technical Data

Manufacturer	Guilin Yikeshi Medical Instrument Co.,Ltd.
Model	MotoSync Pro
Dimensions	21.5cm x 17.5cm x 9cm (Outer box)
Weight	600g
Contra-angle	Contra-angle compatible with rotary and reciprocating instruments, equipped with a 2.35 mm shaft conforming to ISO 1797-1:2011, Type 1
Power supply	Lithium ion battery: 3.7V, 2000mAh
Charger power supply	AC 100-240 V
Frequency	50/60Hz
Charger nominal power input	5VA
Torque range	0.4Ncm – 5Ncm
Speed range	50-2500 rpm
Electrical safety class	Class II
Applied part	B
Ambient conditions	Use:in enclosed spaces Ambient temperature: 5°C-35°C Relative humidity:30%-75%; non-condensing at 0°C Operating altitude 2000m above sea level
Transport and storage conditions	Ambient temperature: -20°C ~ +50°C Relative humidity: 30%-75% non-condensing at >40°C Atmospheric pressure: 70 kPa -106 kPa

12. EMC Tables

Guidance and manufacturer's declaration – electromagnetic emissions

The MotoSync Pro is intended for use in the electromagnetic environment specified below.

The customer or the user of the MotoSync Pro should assure that it is used in such an environment.

Emissions test	Compliance	Electromagnetic environment - guidance
RF emissions CISPR 11	Group 1	The MotoSync Pro uses RF energy only for its internal function. Therefore, its RF emissions are very low and are not likely to cause any interference in nearby electronic equipment.
RF emissions CISPR 11	Class B	The MotoSync Pro is suitable for use in all establishments, including domestic establishments and those directly connected to the public low-voltage power supply network that supplies buildings used for domestic purposes.
Harmonic emissions IEC61000-3-2	Not applicable	
Voltage fluctuations/flicker emissions IEC 61000-3-3	Not applicable	

Guidance and manufacturer's declaration – electromagnetic immunity

The **MotoSync Pro** is intended for use in the electromagnetic environment specified below. The customer or the user of the **MotoSync Pro** should assure that it is used in such an environment.

Immunity test	IEC 60601 test level	Compliance level	Electromagnetic environment - guidance
Electrostatic discharge (ESD) IEC 61000-4-2	± 6 kV contact ± 8 kV air	$\pm 2, 4, 6$ kV contact $\pm 2, 4, 8$ kV air	Floors should be wood, concrete or ceramic tile. If floors are covered with synthetic material, the relative humidity should be at least 30 %.
Electrical fast transients/bursts IEC 61000-4-4	± 2 kV for power supply lines ± 1 kV for input/output lines	Not applicable Not applicable	The test is applicable since the EUT does not have AC/DC power ports and signal/interconnecting cable longer than 3m.
Surge IEC 61000-4-5	± 1 kV line(s) to line(s) ± 2 kV line(s) to earth	Not applicable Not applicable	The test is not applicable since the EUT does not have AC power port.

Voltage dips, short interruptions and voltage variations on power supply lines IEC 61000-4-11	<5% U_T (>95% dip in U_T) for 0.5 cycle	Not applicable	The test is not applicable since the EUT does not have AC power port.
	40% U_T (60% dip in U_T) for 5 cycles	Not applicable	
	70% U_T (30% dip in U_T) for 25 cycles	Not applicable	
	<5% U_T (>95% dip in U_T) for 5 sec	Not applicable	
Power frequency (50/60 Hz) magnetic field IEC 61000-4-8	3 A/m	3 A/m	Power frequency magnetic field should be at levels characteristic of a typical location in a typical commercial or hospital environment.
Note U_T is the a.c. mains voltage prior to application of the test level.			

Guidance and manufacturer's declaration – electromagnetic immunity

The **MotoSync Pro** is intended for use in the electromagnetic environment specified below. The customer or the user of the **MotoSync Pro** should assure that it is used in such an environment.

Immunity test	IEC 60601 test level	Compliance level	Electromagnetic environment - guidance
Conducted RF IEC 61000-4-6 Radiated RF	3 Vrms 150 kHz to 80 MHz	3 V V/m	Portable and mobile RF communications equipment should be used no closer to any part of the MotoSync Pro , including cables, than the recommended separation distance calculated from the equation applicable to the frequency of the transmitter. Recommended separation distance $d = 1.2\sqrt{P}$ $d = 1.2\sqrt{P}$ 80 MHz~800 MHz $d = 2.3\sqrt{P}$ 800 MHz~2.5 GHz Where P is the maximum output power rating of the transmitter in watts (W) according to the transmitter manufacturer and d is the recommended separation distance in meters (m). Field strengths from fixed RF transmitters, as determined by an electromagnetic site survey, ^a should be less than the compliance level in each frequency range. ^b Interference may occur in the vicinity of equipment marked with the following symbol: 
IEC 61000-4-3	3 V/m 80 MHz to 2.5 GHz	3.5 V/m	

NOTE 1: At 80 MHz and 800 MHz, the higher frequency range applies.

NOTE 2: These guidelines may not apply in all situations. Electromagnetic propagation is affected by absorption and reflection from structures, objects and people.

^a Field strengths from fixed transmitters, such as base stations for radio (cellular/cordless) telephones and land mobile radios, amateur radio, AM and FM radio broadcast and TV broadcast cannot be predicted theoretically with accuracy. To assess the electromagnetic environment due to fixed RF transmitters, an electromagnetic site survey should be considered. If the measured field strength in the location in which the **MotoSync Pro** is used exceeds the applicable RF compliance level above, the **MotoSync Pro** should be observed to verify normal operation. If abnormal performance is observed, additional measures may be necessary, such as reorienting or relocating the **MotoSync Pro**.

^b Over the frequency range 150 kHz to 80MHz, field strengths should be less than 3 V/m.

Recommended separation distances between portable and mobile RF communications equipment and the MotoSync Pro

The **MotoSync Pro** is intended for use in an electromagnetic environment in which radiated RF disturbances are controlled. The customer or the user of the **MotoSync Pro** can help prevent electromagnetic interference by maintaining a minimum distance between portable and mobile RF communications equipment (transmitters) and the **MotoSync Pro** as recommended below, according to the maximum output power of the communications equipment.

Rated maximum output power of transmitter W	Separation distance according to frequency of transmitter m		
	150 kHz to 80 MHz	80 MHz to 800 MHz	800 MHz to 2.5 GHz
	$d = 1.2\sqrt{P}$	$d = 1.2\sqrt{P}$	$d = 2.3\sqrt{P}$
0.01	0.12	0.12	0.23
0.1	0.38	0.38	0.73
1	1.2	1.2	2.3
10	3.8	3.8	7.3
100	12	12	23

For transmitters rated at a maximum output power not listed above, the recommended separation distance d in meters (m) can be estimated using the equation applicable to the frequency of the transmitter, where P is the maximum output power rating of the transmitter in watts (W) according to the transmitter manufacturer.

NOTE 1: At 80 MHz and 800 MHz, the separation distance for the higher frequency range applies.

NOTE 2: These guidelines may not apply in all situations. Electromagnetic propagation is affected by absorption and reflection from structures, objects and people.

13.Statement

All rights of modifying the product are reserved to the manufacturer without further notice. The pictures are only for reference. The final interpretation rights belong to **Guilin Yikeshi Medical Instrument Co.,Ltd.**

The industrial design, inner structure, etc, have claimed for several patents by **XPEDENT**, any copy or fake product must take legal responsibilities.

Warranty Card

Name of Customer		(I) For Distributor
Address Details		
Postal Code		
Tel		
Model		
Motor Handpiece No.		
Contra-angle No.		
Purchase Date		
Contact Person		
Date	Maintenance Record	Repairer

 **Guilin Yikeshi Medical Instrument Co.,Ltd.**
 D-8, Guilin National High-tech Zone Information Industrial Park, Chaoyang Road, Qixing District, Guilin, Guangxi, 541004, P.R.China
 Postal Code: 541004
 Tel: 0086 0773 5805522
 Fax: 0086 0773 5805522
 Email: sales@xpediency.cn
 Website: www.xpedent-intl.com

Distributor:	Seal
--------------	------

Warranty Card

Name of Customer		(II) Return to Manufacturer
Address Details		
Postal Code		
Tel		
Model		
Motor Handpiece No.		
Contra-angle No.		
Purchase Date		
Contact Person		
Date	Maintenance Record	Repairer

 **Guilin Yikeshi Medical Instrument Co.,Ltd.**
 D-8, Guilin National High-tech Zone Information Industrial Park, Chaoyang Road, Qixing District, Guilin, Guangxi, 541004, P.R.China
 Postal Code: 541004
 Tel: 0086 0773 5805522
 Fax: 0086 0773 5805522
 Email: sales@xpediency.cn
 Website: www.xpedent-intl.com

Distributor:	Seal
--------------	------

Warranty Instruction

I Period validity

The base, handpiece, power adapter have two years warranty period from the date of purchase.

The contra-angle has one year warranty period.

Other spare parts have six months warranty period.

II Range of warranty

Within the warranty period of validity, we are responsible for any troubles caused by quality problems or products technique and structure.

III The following are beyond our warranty

1. The damage caused by disobeying the operation instruction or lack of the needed condition.
2. The damage caused by unsuitable operation or disassembly without authorization.
3. The damage on product that caused by users' unexpected drop or impact to product.
4. The damage caused by unadvisable transportation or preservation.
5. There isn't the seal of distributor or the warranty card isn't filled in completed.

Warranty Instruction

I Period validity

The base, handpiece, power adapter have two years warranty period from the date of purchase.

The contra-angle has one year warranty period.

Other spare parts have six months warranty period.

II Range of warranty

Within the warranty period of validity, we are responsible for any troubles caused by quality problems or products technique and structure.

III The following are beyond our warranty

1. The damage caused by disobeying the operation instruction or lack of the needed condition.
2. The damage caused by unsuitable operation or disassembly without authorization.
3. The damage on product that caused by users' unexpected drop or impact to product.
4. The damage caused by unadvisable transportation or preservation.
5. There isn't the seal of distributor or the warranty card isn't filled in completed.



EC

REP

Xpedent Austria GmbH

Millennium Park 9 6890 Lustenau Austria

jonathan@xpedent.com



Guilin Yikeshi Medical Instrument Co.,Ltd.

D-8, Guilin National High-tech Zone Information Industrial Park,
Chaoyang Road, Qixing District, Guilin, Guangxi, 541004, P.R.China

Postal Code: 541004

Tel: 0086 0773 5805522

Fax: 0086 0773 5805522

Email: sales@xpediency.cn

Website: www.xpedent-intl.com